

18P80/Nd

LOW FREQUENCY TRANSDUCER

KEY FEATURES

- Real 800 w AES power handling
- Superb sensitivity: 100 dB
- 4" duo technology voice coil
- Carbon fiber reinforced paper cone
- · Neodymium magnet


TECHNICAL SPECIFICATIONS

Nominal diameter 460 mm. 18 in. Rated impedance 8 ohms Minimum impedance 5.8 ohms Power capacity* 800 w AES Program power 1600 w Sensitivity 100 dB 2.83v @ 1m @ 2π Frequency range 25 - 4000 Hz $80/2001 2.8/7 \, ft.^3$ Recom. enclosure vol. Voice coil diameter 100 mm. 4 in. Magnetic assembly weight 4.62 kg 10.16 lb. **BL** factor 21.9 N/A Moving mass 0.146 kg. Voice coil length 20 mm Air gap height 12 mm X damage (peak to peak) 52 mm

THIELE-SMALL PARAMETERS*

Resonant frequency, fs	30 Hz
D.C. Voice coil resistance, Re	5.1 ohms.
Mechanical Quality Factor, Qms	11.55
Electrical Quality Factor, Qes	0.29
Total Quality Factor, Qts	0.29
Equivalent Air Volume to Cms, Vas	411 l
Mechanical Compliance, Cms	193 μm / N
Mechanical Resistance, Rms	2.34 kg / s
Efficiency, ηο (%)	3.7
Effective Surface Area, Sd (m ²)	0.1225 m ²
Maximum Displacement, Xmax***	7.5 mm
Displacement Volume, Vd	918 cm ³
Voice Coil Inductance, Le @ 1 kHz	1.9 mH


FREQUENCY RESPONSE AND DISTORTION



Note: on axis frequency response measured with loudspeaker standing on infinite baffle in anechoic chamber, $1w \otimes 1m$.

H H

DIMENSION DRAWINGS




MOUNTING INFORMATION

Overall diameter	460 mm. 18.11 in.
Bolt circle diameter	438 mm. 17.24 in.
Baffle cutout diameter:	
- Front mount	413 mm. 16.26 in.
- Rear mount	400 mm. 15.75 in.
Depth	201 mm. 7.91 in.
Volume displaced by driver	13 I 0.46 ft. ³
Net weight	7 kg. 15.4 lb.
Shipping weight	8.5 kg. 18.7 lb.

Notes:

FREE AIR IMPEDANCE CURVE



beyma //

Polígono Industrial Moncada II · C/. Pont Sec, 1c · 46113 MONCADA - Valencia (Spain) · Tel. (34) 96 130 13 75 · Fax (34) 96 130 15 07 · http://www.beyma.com · E-mail: beyma@beyma.com ·

^{*}The power capacity is determined according to AES2-1984 (r2003) standard.

Program power is defined as the transducer's ability to handle normal music program.

Program power is defined as the transducer's ability to handle normal music program material
**T-S parameters are measured after an exercise period using a preconditioning power test.

^{***}The Xmax is calculated as (Lvc - Hag)/2 + Hag/3.5, where Lvc is the voice coil length and Hag is the air gap height.